




LH SIDE DETAIL



FRONT DETAIL



BASE DETAIL

3 POLE DP CONTACTORS, 50-60A
WDP50-3L-#, FLA = 50A
WDP60-3L-#, FLA = 60A
(#=COIL VOLTAGE)

COIL DATA:
COILS 24V-600V 50/60Hz
83VA INRUSH, 14VA SEAL
(85-100%) Vs OPERATE
(20-65%) Vs DROPOUT

MAIN CIRCUIT: #10-6 Cu-Wire (WDP50/60)

TIGHTENING TORQUE: 40 LB-IN



WorldWide Electric Corporation

3540 WINTON PLACE
ROCHESTER, NEW YORK 14623 USA
TOLL FREE: 1-800-808-2131

DRAWING SERIES / PARTS:
WDP50-60(3P)
BOXLUG DP CONTACTORS
MECHANICAL DETAILS, 50 - 60A

ENGINEER	JSW	CREATED	20 FEB 16
DRAWN BY	JSW	SCALE	DWG 1:1
CHECKED BY	JSW	SHEET	1 OF 1
DWG NO			

NO.	DATE